

How To...

Light an A-Series Grill



1. We recommend applying vegetable oil to each cooking grate prior to lighting.
2. Ensure all control valves are in the OFF position (parallel to the work shelf).



3. Securely connect the regulator to the propane cylinder and test for leaks according to the Owner's Manual.
 1. QCC Connection: The bright green QCC connector on a regulator threads snugly and easily onto the external threads of the propane cylinder valve by turning the QCC clockwise.
 2. POL Connection: The POL connector on a regulator is inserted into the propane cylinder valve and screws in by turning counter clockwise using the black plastic hand wheel.
4. Open cylinder valve completely and allow system to pressurize - takes about 1 minute.
5. Hold a lit long handled butane lighter gun or fireplace match next to a burner down through the cooking grate and turn the control knob to the ON position. The burner will ignite instantly with a *POOF* sound.
6. Remove lighter and open 2nd control valve - the 2nd burner will light instantly from the 1st.
7. Repeat Steps 4 & 5 for each section of the grill you wish to use.

ALL EQUIPMENT IS FOR OUTDOOR USE ONLY.

526 EAST ROLLING RIDGE DRIVE, BELLEFONTE, PA 16823

P: 814-359-2755

F: 814-359-2621

sales@bigjohngrills.com